

IN THE CLAIMS

Please amend the claims as follows:

1. (original) A method of controlling a circuit arrangement for the AC power supply of a plasma display panel in which the circuit arrangement comprises at least a transistor bridge constituted by the bridge transistors T1, T2, T3, T4, an input voltage U0, a capacitor Cp of the plasma cell and a charging circuit in the form of an auxiliary voltage Uh, a first auxiliary transistor T11 and a first coil L1, and in which said first auxiliary transistor T11 is rendered conductive at the beginning of the charging operation, characterized in that after the first auxiliary transistor T11 has been turned on, the second bridge transistor T2 of the half bridge continues to be turned on for a delay time tv and is turned off after the delay time tv has elapsed.

2. (original) A method of controlling a circuit arrangement for the AC power supply of a plasma display panel, in which the circuit arrangement comprises at least a transistor bridge constituted by the bridge transistors T1, T2, T3, T4, an input voltage U0, a capacitor Cp of the plasma cell and a discharging circuit comprising an auxiliary voltage Uh, a second auxiliary transistor T12 and a second coil L2 and at the beginning of the discharging

operation the second auxiliary transistor T12 is turned on, characterized in that after the second auxiliary transistor T12 has been turned on, the first bridge transistor T1 of the half bridge continues to be turned on for a delay time t_v and is turned off after the delay time t_v has elapsed.

3. (currently amended) A method as claimed in ~~one of the claims 1 or 2~~claim 1, characterized in that the delay time t_v is about $1/8$ of the oscillatory period.

4. (currently amended) A method as claimed in ~~any one of the claims 1 to 3~~claim 1, characterized in that the input voltage U_0 is generated by a DC voltage source.

5. (currently amended) A method as claimed in ~~any one of the claims 1 or 4~~claim 1, characterized in that the auxiliary voltage U_h is applied to an auxiliary capacitor C_s .

6. (original) A method as claimed in claim 5, characterized in that the capacitance of the auxiliary capacitor C_s exceeds by far the capacitance of the capacitor C_p of the plasma cell.

7. (original) A plasma display panel comprising means for controlling a circuit arrangement for the AC power supply of the plasma display panel, the circuit arrangement comprising at least a transistor bridge constituted by the bridge transistors T1, T2, T3, T4, an input voltage U_0 , a capacitor C_p of the plasma cell and a charging circuit comprising an auxiliary voltage U_h , a first auxiliary transistor T11 and a first coil L1 and is provided for turning on the first auxiliary transistor T11 at the beginning of the charging operation, characterized in that after the first auxiliary transistor T11 has been turned on, the second bridge transistor T2 of the half bridge continues to be turned on for a delay time t_v and is turned off after the delay time t_v has elapsed.